
Factory Reset Options for Soft and Hard Reset of Lumenetix Controllers and Modules

CAUTION: PLEASE NOTE ANY DMX ADDRESS BEFORE PERFORMING THIS FUNCTION AS THIS WILL CLEAR AND RESET TO ADDRESS 1.

OPTION-1 — SOFT RESET

To perform a “soft reset “of the controller (module), the steps would be as follows:

1. Open the Lumenetix-arya Tunable Color 2.0 iOS App.
2. Do not log in (go ahead and skip this step).
3. ‘Open’ the light to the main screen.
4. Click on the Edit button (top right of the screen).
5. Scroll to the bottom and click on the factory reset option.
6. It will ask you to enter the password (“Please consult your Lumenetix Rep”) when asked.
7. The light will reset to the factory default.

OPTION-2 — HARD RESET

To perform a “hard reset “of the controller (module), you will need a 7-wire cable connected to the module (part number 28.002.002.01). The steps for doing so are as follows:

1. Shut down the iOS App completely by swiping it closed/away.
2. Power off controller (module).
3. Connect the 7-wire Input Universal Control Cable to the controller.
4. Leave all 7 wires OPEN.
5. Power on controller (module).
6. Leave Brown, Orange, and White / Orange wires OPEN.
7. Manually short together the Violet, Gray, Blue, and White wires.
8. Manually open the Violet, Gray, Blue, White Wires.
9. Wait 30 seconds.
10. Power off controller (module).
11. Remove 7-wire Input Universal Control Cable from the controller.